

Nomenclature - Part List
Amplificateurs - Amplifiers P S S
Type : 7-M Date : 05-01-1998

Reference	Valeur – Value	Reference	Valeur – Value
C 5, C 9, C 36	1 000 μ F 16V	R 34	4 700 Ω
C6,C7,C8,C15,C18,C24,C28	47 μ F 63V	R 6	15 000 Ω
C10, C11, C12, C 14, C 17	4,7 μ F 63V	R 3 (1%), R 12, R 58	39 000 Ω
C 13, C 16, C 25, C 26, C 19	39 pF	R 4 (1%)	22 000 Ω
C 23, C 31	270 pF	R 7, 16	33 000 Ω
C 20, C 30	10 nF	R 13	2 700 Ω
C 21, C 32, C 34, C 35	220 nF	R 14, R 18	82 000 Ω
C 27, C 29	47 nF	R 15	10 000 Ω
CI 1, CI 2	UA 741	R 17	6 200 Ω
CTN 1, CTN 2 (3%)	100 000 Ω (RTC)	R 2 (1%)	4 700 Ω
Régulateur – Fan Regulator	LM317T	R 23, R 26, R 40	18 000 Ω
D 1, D 2, D 3, D 4	BY 550-600V 5A	R 1, R 5, R 9, R 10, R 11	1 800 Ω
D5, D6, D7, D8, D10, D11, D12, D13, D14, D15, D19, D21, D22, D23, D24, D25, D26, D27, D29, D30, D31	1N 4004	R 31, R 45, R 48, R 49	120 Ω
D 9, D 18 (3mm Led)	Verte/Green	R 32, R 47	47 Ω
D 16, D 28 (3mm Led)	Rouge/Red	R 33, R 46	1 000 Ω - 2 W
D 20 (3mm Led)	Jaune/Yellow	R 39 (2W), R 42, R 43 (2W)	680 Ω
T 1, T 4, T 10	MPSA 06	R 44	470 Ω
T2, T3, T6, T7, T14, T15	MPSA 56	R 54	10 Ω - 3 W
T 5	TIP 41 A/B/C	R 24, R 29	3 300 Ω
T 8	TIP 48 - 49 – 50	R19, R 20, R 21, R 55	47 000 Ω
		D 33, D34 (Zener)	15 V

All transistors are from MOTOROLA – Tous les transistors sont de marque MOTOROLA

Reference	SAP 2125 / SAP 2150	SAP 2200	SAP 2300 / SAP 2400	SAP 2600
C1,C2,C3,C4	4700 μ F 63V	4700 μ F	2x4700 μ F 63V	2x4700 μ F 100V
R 8	8,2K (2125)/10K (2150)	12 000 Ω	15 K (2300)/18 K (2400)	18 000 Ω
R 22	18 000 Ω	18 000 Ω	18 000 Ω	18 000 Ω
R 25	18 000 Ω	22 000 Ω	22 K (2300)/24 K (2400)	27 000 Ω
R 28	1 800 Ω	1 800 Ω	2 700 Ω	2 700 Ω
R 30	68 Ω	68 Ω	68 Ω (2300)/47 Ω (2400)	47 Ω
R 41	560 (2125)/470 (2150)	470 Ω	330 Ω	330 Ω
R 55, R 56	24 000 Ω /27 000 Ω	33 000 Ω	39 000 Ω /47 000 Ω	56 000 Ω
T 9	TIP 41 C	TIP 41 C	MJE 13007	MJE 13007
T 15	TIP 42 C	TIP 42 C	MJE 5852	MJE 5852
T 11 à T 13 & 20	1 x MJ 15003	2 x MJ15003	3 ou/or 4 x MJ 15003	4 x MJ 15024
T 16 à T 19	1 x MJ 15003	2 x MJ15003	3 ou/or 4 x MJ 15003	4 x MJ 15024
R 35 à R 38	1 x 0,22 Ω 3W	2 x 0,33 Ω 3W	3 ou/or 4 x 0,33 Ω 3W	4 x 0,33 Ω 3W
R 50 à R 53	1 x 0,22 Ω 3W	2 x 0,33 Ω 3W	3 ou/or 4 x 0,33 Ω 3W	4 x 0,33 Ω 3W
C 33	47 nF	47 nF	47 nF	47 nF
D 32 (Zener)	27 V(2125)/30 V(2150)	33 V	36 V(2300)/ 39 V(2400)	43 V
F 2, F 3	3,15 A rapide/fast	4 A rapide/fast	5 A - 6,3 A rapide/fast	6,3 A rapide/fast
L 1	0.1 mH	0.1 mH	0.1 mH	0.1 mH