Schematic Ref. No.	Part No.	Description
	BA04210A	Logic P.C.B. Ass'y
	— Logic —	
IC401, 402 403	0B06178A	IC μPD4011C
IC404	0B06143A	IC μPD4001C
IC405	0B06124B	IC RC4558D
IC406	0B06144A	IC μPD4066C
IC407	0B06192A	Regulator +12V μA7812
IC408	0B06193A	Regulator -12V μA7912
Q401, 405 406, 407 408, 409 410, 411 412, 413 414, 417 419, 420 421, 422 423, 429 430, 435 447	0B06100A	Transistor 2SC945 (A)
Q402, 403 404, 415 416, 418 428, 433	0B06013A	Transistor 2SA733
Q424, 426	0B06020A	Transistor 2SC1096
Q425, 427	0B06012A	Transistor 2SA634
Q432	0B06069A	Transistor 2SB564
Q434	0B06066A	Transistor 2SD471
ZD403, 404	0B06231A	Zener Diode 11V
D401-437 442-444 471, 473 476	0B01909A	Silicon Diode 1S1555 (43 pcs.)
D438, 439	0B06109A	Silicon Diode GP08B
D470	0B06183A	Diode Bridge RB151
VR401	0B03832A	Semi-fixed Volume 100K
VR402, 403	0B03831A	Semi-fixed Volume 5K
R401, 402 403, 404 405, 406 407, 408 409, 410 411, 412 416, 417 418, 419 421, 422 423, 424 425, 429 430, 434 436, 440 441, 442 447, 448 449, 450 457, 458 474, 475 481, 482 486, 513 517, 520 522	0B05627A	Carbon Resistor 330K ERD-25T J
R413, 466 476, 507 514, 607	0B05509A	Carbon Resistor 33K ERD-25T J
R414, 437 451-456 502	0B05615A	Carbon Resistor 22K ERD-25T J (9 pcs.)
R415, 488	0B09263A	Carbon Resistor 12K ERD-25T J
R420, 471 472	0B09049A	Fail Safe Type Resistor 22 ERD-14F J
R426, 504	0B01682A	Carbon Resistor 6.8K ERD-25T J
R427, 428 446, 515 516	0B05776A	Carbon Resistor 1M ERD-25T J
R431	0B05698A	Carbon Resistor 1.5K ERD-25T J
R432, 433 494, 498 503, 509	0B05671A	Carbon Resistor 2.2M ERD-25T J
R435	0B05784A	Carbon Resistor 560K ERD-25T J
R438, 439 491	0B05625A	Carbon Resistor 220K ERD-25T J
R444	0B09367A	Metal Film Resistor 174K SN14K2E F
R445	0B09366A	Metal Film Resistor 287K SN14K2EF
R459, 464 493, 505 510, 511 523, 525	0B01889A	Carbon Resistor 100K ERD-25T J
R461	0B09328A	Metal Film Resistor 9.1K SN14K2E F
R463	0B09365A	Metal Film Resistor 4.32K SN14K2E F
R465	0B09340A	Metal Film Resistor 15K SN14K2E F
R467	0B05743A	Carbon Resistor 27K ERD-25T J
R468, 469	0B01856A	Carbon Resistor 8.2K ERD-25T J
R470	0B05578A	Carbon Resistor 180 ERD-25T J
R473, 477 485	0B01681A	Carbon Resistor 3.3K ERD-25T J
R478, 487	0B01854A	Carbon Resistor 39K ERD-25T J
R479, 490 506, 521	0B01888A	Carbon Resistor 10K ERD-25T J
R480, 499	0B05508A	Carbon Resistor 56K ERD-25T J
R483, 484 508	0B01857A	Carbon Resistor 1K ERD-25T J
R489	0B05640A	Carbon Resistor 180K ERD-25T J
R492	0B05680A	Carbon Resistor 1.8M ERD-25T J
R495, 500 501	0B05692A	Carbon Resistor 68K ERD-25T J
R496	0B01887A	Carbon Resistor 5.6K ERD-25T J
R497	0B09320A	Carbon Resistor 820K ERD-25T J
R512	0B09381A	Fail Safe Type Resistor 2 RDF-25S J
R518	0B09217A	Fail Safe Type Resistor 5.6 RDF-25S J
R519	0B05794A	Carbon Resistor 680 ERD-25T J
R524	0B05621A	Carbon Resistor 120K ERD-25T J
R526	0B05560A	Carbon Resistor 18K ERD-25T J
R528, 530	0B09215A	Fail Safe Type Resistor 100 RDF-25S J
R529, 531	0B09321A	Fail Safe Type Resistor 4.7 RDF-25S J
R590	0B09216A	Fail Safe Type Resistor 10 RDF-25S J
C401, 421	0B01412A	Electrolytic Capacitor 10μ 16V
C402, 403 405, 406	0B05556A	Mylar Capacitor 4700P 50V
C404	0B05582A	Mylar Capacitor 0.022μ 50V J
C407	0B00093A	Mylar Capacitor 0.1μ 50V
C408	0B01405A	Electrolytic Capacitor 1μ 50V
C409	0B09166A	Mylar Capacitor 3300P 50V
C410	0B00610A	Mylar Capacitor 0.15μ 50V
C411, 414	0B01676A	Mylar Capacitor 0.056μ 50V
C412, 413	0B09324A	Electrolytic Capacitor 3.3μ 16V (LN)
C415, 422	0B09223A	Electrolytic Capacitor 1μ 50V (LN)
C416	0B09173A	Electrolytic Capacitor 4.7μ 16V (LN)
C417	0B09277A	Ceramic Capacitor 10P 50V J
C418, 420	0B05513A	Mylar Capacitor 0.033μ 50V
C419	0B01502A	Electrolytic Capacitor 330μ 16V
C423, 424 425	0B01406A	Electrolytic Capacitor 2200μ 16V
C426	0B09374A	Electrolytic Capacitor 6800μ 25V
C427	0B05654A	Electrolytic Capacitor 2200μ 25V
C457	0B09286A	Ceramic Capacitor 470P 50V K
CN5, 11	0B08645A	9P-T Post
CN6	0B08642A	6P-T Post
CN7	0B08643A	7P-T Post
CN8	0B08644A	8P-T Post
CN9	0B08653A	3P-T Post
CN10	0B08655A	11P-T Post
	— RAMM —	
IC409	0B06127A	IC RC4559D
IC410	0B06215A	IC TC4049BP
IC411	0B06143A	IC μPD4001C
IC412	0B06214A	IC TC4071BP
IC413	0B06213A	IC TC4013BP
IC414	0B06212A	IC TC4510BP
IC415	0B06211A	IC TC5022BP
Q431	0B06060A	Transistor 2SA473
Q436	0B06070A	Transistor 2SC1636
Q437	0B06100A	Transistor 2SC945 (L)
Q438-446	0B06013A	Transistor 2SA733 (9 pcs.)
ZD401	0B06235A	Zener Diode 39V
ZD402	0B06230A	Zener Diode 5V
D440, 441	0B06109A	Silicon Diode GP08B
D445-454 456-467 474, 475	0B06181A	Silicon Diode 1SS53 (24 pcs.)
R527	0B05675A	Carbon Resistor 3.9K ERD-25T J
R532, 534 546, 563 465, 570 572-580 602	0B01889A	Carbon Resistor 100K ERD-25T J (16 pcs.)
R533, 535 543, 545 568, 569 571	0B05509A	Carbon Resistor 33K ERD-25T J
R536	0B05622A	Carbon Resistor 2.2K ERD-25T J
R537	0B01679A	Carbon Resistor 100 ERD-25T J
R538	0B05621A	Carbon Resistor 120K ERD-25T J
R539	0B05623A	Carbon Resistor 1.2K ERD-25T J
R540, 550 551, 554 555, 567 608	0B05627A	Carbon Resistor 330K ERD-25T J
R541	0B05508A	Carbon Resistor 56K ERD-25T J
R542, 581	0B01888A	Carbon Resistor 10K ERD-25T J
R544, 562	0B01857A	Carbon Resistor 1K ERD-25T J
R547, 549	0B05671A	Carbon Resistor 2.2M ERD-25T J
R548	0B05615A	Carbon Resistor 22K ERD-25T J
R552, 553 558	0B05776A	Carbon Resistor 1M ERD-25T J
R560	0B05625A	Carbon Resistor 220K ERD-25T J
R565, 566	0B05676A	Carbon Resistor 390K ERD-25T J
R582-588	0B09320A	Carbon Resistor 820K ERD-25T J (7 pcs.)
R589	0B01684A	Carbon Resistor 470K ERD-25T J
C429, 430	0B09313A	Electrolytic Capacitor 100μ 50V
C431, 432 436	0B05652A	Mylar Capacitor 4700P 50V J
C434, 444 446	0B01405A	Electrolytic Capacitor 1μ 50V
C434	0B01863A	Electrolytic Capacitor 3.3μ 50V
C435	0B05557A	Mylar Capacitor 0.015μ 50V J
C437	0B09222A	Electrolytic Capacitor 0.47μ 16V (LN)
C438	0B09287A	Ceramic Capacitor 680P 50V K
C439	0B00610A	Mylar Capacitor 0.15μ 50V J
C440, 441	0B05583A	Mylar Capacitor 0.033μ 50V J
C442, 443	0B09220A	Electrolytic Capacitor 0.22μ 50V (LN)
C447	0B09285A	Ceramic Capacitor 330P 50V K
C459	0B09187A	Electrolytic Capacitor 1μ 50V (BP)
C461	0B01180A	Ceramic Capacitor 330P 100V
	— Azimuth Detector —	
IC416	0B06216A	IC μPC4556C
Q448, 451	0B06100A	Transistor 2SC945 (L)
D468, 469	0B06181A	Silicon Diode 1SS53
VR404, 405	0B09107A	Semi-fixed Volume 500K
R591, 593 601	0B01889A	Carbon Resistor 100K ERD-25T J
R592, 594 609	0B05625A	Carbon Resistor 220K ERD-25T J
R595, 596 610	0B05627A	Carbon Resistor 330K ERD-25T J
R597, 599 600	0B01888A	Carbon Resistor 10K ERD-25T J
R598	0B01681A	Carbon Resistor 3.3K ERD-25T J
C448, 449	0B01412A	Electrolytic Capacitor 10μ 16V
C450, 451	0B01802A	Mylar Capacitor 2200P 50V J
C452	0B09221A	Electrolytic Capacitor 1.5μ 50V (LN)
	— Miscellaneous —	
	0B07827E	Logic P.C.B.
	0J04030B	Heat Sink (1 pce.)
	0E00860A	BT Screw M3x6 Philips Binding Head (2 pcs.)
	0E00896A	Screw M3x6 Philips Binding Head (Black Chromate) (2 pcs.)
	0E00507A	Nut Hex. M3 (2 pcs.)

Schematic Ref. No.	Part No.	Description	
	BA04095A	**Fuse P.C.B. Ass'y (U.S.A. & Canada)**	
	0B07842A	Fuse P.C.B.	
F1, 2, 3	0B08374A	Fuse 1A 250V	
	0B08342A	Spark Killer	(1 pce.)
	0M04075B	Fuse Caution A112	(1 pce.)
	0M04078B	Fuse Label 1A x 2	(1 pce.)
	0M03782A	Fuse Label 1A	(1 pce.)
	0J03834B	Fuse P.C.B. Holder	(1 pce.)
	0E00606A	Screw M3x6 philips Pan Head (3A)	(2 pcs.)
	0E00752A	Eyelet	(6 pcs.)
	BA04096A	**Fuse P.C.B. Ass'y (Japan)**	
	0B07842A	Fuse P.C.B.	
F1, 2, 3	0B08686A	Fuse 1A 250V	
	0B08363A	Spark Killer	(1 pce.)
	0M04078B	Fuse Label 1A x 2	(1 pce.)
	0M03782A	Fuse Label 1A	(1 pce.)
	0J03834B	Fuse P.C.B. Holder	(1 pce.)
	0E00606A	Screw M3 x 6 Philips Pan Head (3A)	(2 pcs.)
	0E00752A	Eyelet	(6 pcs.)
	BA04097B	**Fuse P.C.B. Ass'y (Others)**	
	0B07842A	Fuse P.C.B.	
F1, 2, 3	0B08263A	Fuse T 315mA 250V	
F4, 5	0B08347A	Fuse T 1A 250V	
	0B08349A	Fuse Clip	(10 pcs.)
	0B08240A	Spark Killer	(1 pce.)
	0M04073A	Fuse Label 315mA	(1 pce.)
	0M04131A	Fuse Label 1A x 2	(1 pce.)
	0M04074A	Fuse Label 315mA x 2	(1 pce.)
	0J03834B	Fuse P.C.B. Holder	(1 pce.)
	0E00606A	Screw M3 x 6 Philips Pan Head (3A)	(2 pcs.)
	0E00752A	Eyelet	(6 pcs.)
	BA04098B	**Fuse P.C.B. Ass'y (UK & Australia)**	
	0B07842A	Fuse P.C.B.	
F1	0B08665A	Fuse T 160mA 250V	
F2, 3	0B08263A	Fuse T 315mA 250V	
F4, 5	0B08347A	Fuse T 1A 250V	
	0B08349A	Fuse Clip	(10 pcs.)
	0B08240A	Spark Killer	(1 pce.)
	0M04066A	Fuse Label 160mA	(1 pce.)
	0M04131A	Fuse Label 1A x 2	(1 pce.)
	0M04074A	Fuse Label 315mA x 2	(1 pce.)
	0J03834B	Fuse P.C.B. Holder	(1 pce.)
	0E00606A	Screw M3 x 6 Philips Pan Head (3A)	(2 pcs.)
	0E00752A	Eyelet	(6 pcs.)
	BA04105B	**Fuse P.C.B. Ass'y (220V Class 2)**	
	0B07842A	Fuse P.C.B.	
F1	0B08665A	Fuse T 160mA 250V	
F2, 3	0B08263A	Fuse T 315mA 250V	
F4, 5	0B08347A	Fuse T 1A 250V	
	0B08349A	Fuse Clip	(10 pcs.)
	0B08445A	Spark Killer	(2 pcs.)

7.6. Fuse P.C.B. Ass'y




Fig. 7.6.1 U.S.A., Canada & Japan




Fig. 7.6.2 Others




Fig. 7.6.3 UK & Australia




Fig. 7.6.4 220 V Class 2

Schematic Ref. No.	Part No.	Description	
	0M04066A	Fuse Label 160mA	(1 pce.)
	0M04131A	Fuse Label 1A x 2	(1 pce.)
	0M04074A	Fuse Label 315mA x 2	(1 pce.)
	0J03834B	Fuse P.C.B. Holder	(1 pce.)
	0E00606A	Screw M3 x 6 Philips Pan Head	(3A) (2 pcs.)
	0E00752A	Eyelet	(6 pcs.)

7.7. Pin Jack P.C.B. Ass'y




Fig. 7.7

7.8. Auto Shut-off P.C.B. Ass'y




Fig. 7.8

Note: Diode is 1SS53 unless otherwise specified.

7.9. Volume P.C.B. Ass'y




Fig. 7.9

7.10. Auto Azimuth P.C.B. Ass'y




Fig. 7.10

Schematic Ref. No.	Part No.	Description		Schematic Ref. No.	Part No.	Description	
	BA04176A	**Pin Jack P.C.B. Ass'y**		D701,702	0B06181A	Silicon Diode	1SS53
				801,802			
	0B07835A	Pin Jack P.C.B.		901,902			
FC8	0B05238A	5P Flat Cable 50mm		903,904			
	0B08709A	Jack Unit	(1 pce.)	905,906			
	0E00037A	Earth Lug B-5	(1 pce.)	VR901,902	0B09107A	Semi-fixed Volume	500K
				R701,801	0B05625A	Carbon Resistor	220K ERD-25T J
	BA04070A	**Auto Shut-off P.C.B. Ass'y**		917,919			
				R702,802	0B01889A	Carbon Resistor	100K ERD-25T J
	0B07839A	Auto Shut-off P.C.B.		929,930			
Q449	0B01872A	Transistor	2SC945 (L)	936,937			
Q450	0B06228A	Photo Transistor	PH104	R703,803	0B01888A	Carbon Resistor	10K ERD-25T J
D470	0B06181A	Silicon Diode	1SS53	913,922			
R603	0B05671A	Carbon Resistor	2.2M ERD-25T J	R704,804	0B05627A	Carbon Resistor	330K ERD-25T J
R604	0B05615A	Carbon Resistor	22K ERD-25T J	904,927			
R605	0B09215A	Fail Safe Type Resistor	100 RDF-25S J	R705,706	0B05509A	Carbon Resistor	33K ERD-25T J
R606	0B01888A	Carbon Resistor	10K ERD-25T J	805,806			
C453	0B01405A	Electrolytic Capacitor	1μ 50V	905,906			
PL407	0B08552A	Lamp	12V 25mA	907,909			
				910,925			
	BA04069A	**Volume P.C.B. Ass'y**		R707,807	0B05671A	Carbon Resistor	2.2M ERD-25T J
				920,923			
	0B07836A	Volume P.C.B.		928			
VR001	0B07231A	Volume	100K (A)x2	R901,902	0B05776A	Carbon Resistor	1M ERD-25T J
VR002	0B07279A	Volume	100K (A)x2	903,918			
VR003	0B07259A	Volume	5K (A)x2	R908	0B01681A	Carbon Resistor	3.3K ERD-25T J
R191,291	0B09263A	Carbon Resistor	12K ERD-25T J	R911,912	0B01887A	Carbon Resistor	5.6K ERD-25T J
R192,292	0B05622A	Carbon Resistor	2.2K ERD-25T J	R914,916	0B05615A	Carbon Resistor	22K ERD-25T J
FC3	0B05237A	5P Flat Cable	200mm	924,931			
				R915	0B09380A	Carbon Resistor	1.5M ERD-25T J
	BA04208A	**Azimuth P.C.B. Ass'y B**		R921	0B05692A	Carbon Resistor	68K ERD-25T J
				R926	0B01682A	Carbon Resistor	6.8K ERD-25T J
	0B07872A	Azimuth P.C.B.		R932	0B05626A	Carbon Resistor	150K ERD-25T J
IC901,905	0B06124B	IC	RC4558D	R933	0B05641A	Carbon Resistor	47K ERD-25T J
IC902	0B06216A	IC	μPC4556C	C701,801	0B01405A	Electrolytic Capacitor	1μ 50V
IC903	0B06213A	IC	TC4013BP	901,902			
IC904	0B06244A	IC	μPD4073C	C702,802	0B01412A	Electrolytic Capacitor	10μ 16V
Q901,902	0B01872A	Transistor	2SC945(L)	C704,804	0B01802A	Mylar Capacitor	2200P 50V J
905,906				C705,805	0B01676A	Mylar Capacitor	0.056μ 50V
907,909				C903	0B01389A	Electrolytic Capacitor	4.7μ 16V
910,913				C904	0B05772A	Tantalum Capacitor	0.22μ 35V
Q903	0B06066A	Transistor	2SD471	CN10	0B08656A	2P-T Post	
Q904	0B06069A	Transistor	2SB564				
Q908	0B06013A	Transistor	2SA733				

7.11. Control Switch P.C.B. Ass'y




Fig. 7.11

7.12. Lamp P.C.B. A Ass'y




Fig. 7.12

7.13. Lamp P.C.B. B Ass'y




Fig. 7.13

7.14. Lamp P.C.B. C Ass'y




Fig. 7.14

Schematic Ref. No.	Part No.	Description	Schematic Ref. No.	Part No.	Description
	BA04071A	**Control Switch P.C.B. Ass'y**		**BA04062A**	**Lamp P.C.B. B Ass'y**
	0B07832A	Control Switch P.C.B.		0B07838A	Lamp P.C.B. B
SW401-406	0B07219A	Semi-Switch	PL408	0B08586A	Lamp 12V 60mA
PL401-406	0B08552A	Lamp 12V 25mA			
CN7	0B08631B	7P-H Connector A Ass'y		**BA04063A**	**Lamp P.C.B. C Ass'y**
CN8	0B08630B	8P-H Connector A Ass'y			
				0B07840A	Lamp P.C.B. C
	BA04072A	**Lamp P.C.B. A Ass'y**	PL409	0B08586A	Lamp 12V 60mA
	0B07837A	Lamp P.C.B. A			
PL001, 002	0B08552A	Lamp 12V 25mA			

7.15. Indicator P.C.B. A Ass'y




Fig. 7.15 Note: Diode is 1SS53 unless otherwise specified.

7.16. Indicator P.C.B. B Ass'y




Fig. 7.16 Note: Diode is 1SS53 unless otherwise specified.

Schematic Ref. No.	Part No.	Description
	BA04061A	**Indicator P.C.B. A Ass'y**
	0B07829A	Indicator P.C.B. A
D927-932	0B06181A	Silicon Diode 1SS53 (6 pcs.)
R761-770	0B01684A	Carbon Resistor 470K ERD-25T J
861-870		(30 pcs.)
945-954		
BG901	0B08640A	Display Unit FIP50A13Y
CN5	0B08638A	9P-H Connector Ass'y
CN12	0B08636A	7P-H Connector C Ass'y
CN13	0B08637A	8P-H Connector B Ass'y
CN14	0B08639A	10P-H Connector Ass'y
CN15	0B08635A	7P-H Connector B Ass'y
	BA04065A	**Indicator P.C.B. B Ass'y**
	0B07830B	Indicator P.C.B. B
IC909, 910	0B06218A	IC TC4022BP
IC911	0B06219A	IC TC4081BP
IC912	0B06215A	IC TC4049BP
Q751-760	0B06013A	Transistor 2SA733 (26 pcs.)
851-860		
909-914		
Q908	0B06100A	Transistor 2SC945
D751-760	0B06181A	Silicon Diode 1SS53 (29 pcs.)
851-860		
918-926		
ZD903	0B06241A	Zener Diode 6.8V
R751-760	0B01888A	Carbon Resistor 10K ERD-25T J
851-860		(23 pcs.)
930-932		
R929	0B05691A	Carbon Resistor 390 ERD-25T J
R933, 935	0B01887A	Carbon Resistor 5.6K ERD-25T J
937, 939		
941, 943		
R934, 936	0B09263A	Carbon Resistor 12K ERD-25T J
938, 940		
942, 944		
C905, 906	0B09290A	Ceramic Capacitor 0.01μ 50V J
CN12, 15	0B08643A	7P-T Post
CN13	0B08644A	8P-T Post
CN14	0B08646A	10P-T Post
CN16	0B08642A	6P-T Post
FC901	0B05239A	8P Flat Cable 50mm

Schematic Ref. No.	Part No.	Description
	BA04066A	**Indicator P.C.B. C Ass'y**
	0B07831B	Indicator P.C.B. C
IC901	0B06144A	IC μPD4066C
IC902	0B06219A	IC TC4081BP
IC903	0B06215A	IC TC4049BP
IC904	0B06217A	IC RC4560D
IC905	0B06224A	IC TC4023BP
IC906	0B06178A	IC μPD4011C
IC907	0B06223A	IC TC4040BP
IC908	0B06216A	IC RC4556C
Q901, 904	0B06100A	Transistor 2SC945
Q902, 903	0B06013A	Transistor 2SA733
905, 906		
907		
ZD901	0B06230A	Zener Diode 5V
ZD902	0B06233A	Zener Diode 10V
D901-917	0B06181A	Silicon Diode 1SS53 (17 pcs.)
VR901	0B07257A	Semi-fixed Volume 100K
R901, 907	0B01889A	Carbon Resistor 100K ERD-25T J
913, 914		
915		
R902	0B05578A	Carbon Resistor 180 ERD-25T J
R903	0B01856A	Carbon Resistor 8.2K ERD-25T J
R904	0B09299A	Metal Film Resistor 511K SN14K2E F
R905	0B09319A	Metal Film Resistor 36.5K SN14K2E F
R906	0B05509A	Carbon Resistor 33K ERD-25T J
R908, 916	0B01888A	Carbon Resistor 10K ERD-25T J
917, 920		
921, 922		
923, 924		
R909	0B09300A	Metal Film Resistor 150K SN14K2E F
R910	0B09298A	Metal Film Resistor 64.9K SN14K2E F
R911, 912	0B05743A	Carbon Resistor 27K ERD-25T J
919		
R918	0B05692A	Carbon Resistor 68K ERD-25T J
R925	0B01857A	Carbon Resistor 1K ERD-25T J
R926	0B05698A	Carbon Resistor 1.5K ERD-25T J
R927	0B01682A	Carbon Resistor 6.8K ERD-25T J
R928	0B09263A	Carbon Resistor 12K ERD-25T J
C901	0B09191A	PP Capacitor 4700P 100V G
C902	0B09312A	PP Capacitor 0.01μ 100V G
C903	0B09322A	PP Capacitor 330P 100V G
C904	0B09290A	Ceramic Capacitor 0.01μ 50V J
CN4	0B08633A	6P-H Connector B Ass'y
CN6	0B08634A	6P-H Connector C Ass'y
CN16	0B08632A	6P-H Connector A Ass'y

7.17. Indicator P.C.B. C Ass'y




Fig. 7.17 Note: Diode is 1SS53 unless otherwise specified.

8. MECHANISM ASS'Y AND PARTS LIST

8.1. Synthesis




Fig. 8.1